


LED converter 350 mA, DALI dimmable (digital)

Article no. 17684020

Light.
For Generations.**Tender**

LED-Konverter 350 mA, DALI dimmbar (digital). This converter is equipped with safety devices which protect it against overvoltage, short-circuit as well as thermal and electric overloads. The input and output terminals are suitable for cables with a cross-section of up to 0.75-1.5 mm². Material: Plastic, Degree of protection: according to DIN EN 60529 IP20, Protection class: (EN 61140) II, Voltage: 230V AC 50Hz, Power: 7W, Control: DALI-2.

Product Benefits

We guarantee: No afterglow of the LEDs. A weak afterglow of the LED lights in the switched-off state is an undesirable, unacceptable effect. With our new LED converter, this is eliminated. This reduces troubleshooting as well as installation efforts and offers optimal operational reliability. The converter is available in three versions and additionally already integrated in the BB sets.

Article data	
Article no.	17684020
GTIN	4251433951209
Short description	LED converter 350 mA, DALI dimmable (digital)
Material	Plastic
Length	130 mm
Width	42 mm
Height	22 mm
Scope of delivery	Plug&Play version with 110 mm P&P output cable
Weight	0.104 kg

LED converter 350 mA, DALI dimmable (digital)

Article no. 17684020

Light.
For Generations.

Operating technology of driver	
AC nominal voltage min	220 V
AC nominal voltage max	240 V
DC nominal voltage min	186 V
DC nominal voltage max	250 V
Current	350 mA
Protection class	II
Degree of protection	IP20
Starting current	1A
Power min	2.8 W
Power	7 W
Control	DALI-2
Flickerfrei	Ja
Environment temperature (ta)	-20 °C bis +50 °C
Measure point (tc)	max. +70 °C
Version	Plug&Play + connection box

Packing data	
Gross weight	0.146 kg
Length of packaging	140 mm
Packaging width	110 mm
Packaging height	120 mm
Disposal at end of life	<p>This product must not be disposed of with household waste. You are obliged, to dispose of such electrical waste separately.</p> <p>By disposing of electrical waste and other old or defective electronics separately, you support recycling or other forms of re-use. In that way you help to take care and to avoid that harmful substances get into the environment.</p>